



NMOS Electrical Characteristics (T_j=25℃)

Parameter	Symbol
Static Parameter	
Drain-Source Breakdown Voltage	BV _{DSS}
Zero Gate Voltage Drain Current	I _{DSS}

V_{DS}=100V, V_{GS}=0V, T_j=150℃

-

-

100



YJS03NP10A

PMOS Electrical Characteristics ($T_J=25$ unless otherwise noted)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
Static Parameter						
Drain-Source Breakdown Voltage	BV_{DSS}	$V_{GS}=0V, I_D=-250$	-100	-	-	V
Zero Gate Voltage Drain Current	I_{DSS}	$V_{DS}=-100V, V_{GS}=0V$	-	-	-1	
		$V_{DS}=-100V, V_{GS}=0V, T_J=150$	-	-	-100	
Gate-Body Leakage Current	I_{GSS}	$V_{GS}= \pm 20V, V_{DS}=0V$	-	-	± 100	nA
Gate Threshold Voltage	$V_{GS(th)}$	$V_{DS}=V_{GS}, I_D=-250$	-1	-1.7	-2.5	V
Static Drain-Source On-Resistance	$R_{DS(on)}$	$V_{GS}=-10V, I_D=-3A$	-	85	110	m
		$V_{GS} \text{ re } W^*nBT/F5 \text{ 7.92 Tf g0 G[}$				

NMOS Typical Electrical and Thermal Characteristics Diagrams






Figure 1. Output Characteristics

Figure 2. Transfer Characteristics





YJS03NP10A




Figure 7. $R_{DS(on)}$ VS Drain Current




Figure 8. Forward characteristics of reverse diode




Figure 9. Normalized breakdown voltage




Figure 10. Normalized Threshold voltage




Figure 11. Current dissipation




Figure 12. Power dissipation




Figure 13. Maximum Transient Thermal Impedance




Figure 14. Safe Operation Area

PMOS Typical Electrical and Thermal Characteristics Diagrams




Figure 1. Output Characteristics




Figure 2. Transfer Characteristics




Figure 5. On-Resistance vs Gate to Source Voltage




Figure 6. Normalized On-Resistance




Figure 7. $R_{DS(on)}$ VS Drain Current




Figure 8. Forward characteristics of reverse diode




Figure 9. Normalized breakdown voltage





Figure 10. Normalized Threshold voltage



SOP-8 Package information





Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or IYaor controlleranpS4(l)-14/F5 9.12 Tf13(e)30(si)-14(g013(e)30(si7hS4(l)-14/(n)r)-8(o)30A110 Tm0 g0 G[d]3(e)e)30(n)