



HS1AB THRU HS1MB

Surface Mount High Efficient Rectifier

Features

- ✓ Low profile package
- ✓ Ideal for automated placement
- ✓ Glass passivated chip junction
- ✓ High forward surge capability
- ✓ Super fast reverse recovery time
- ✓ Meets MSL level 1 , per J-STD-020 , LF maximum peak of 260 °C

Typical Applications

For use in high frequency rectification of power supplies , inverters , converters , and freewheeling diodes for consumer and telecommunication.

Mechanical Data

- ✓ Package: DO-214AA (SMB)
- Molding compound meets UL 94 V-0 flammability rating , RoHS-compliant , halogen-free
- ✓ Terminals: Tin plated leads , solderable per J-STD-002 and JESD22-B102
- ✓ Polarity: Cathode line denotes the cathode end

Maximum Ratings (Ta = 25°C Unless otherwise specified)

Device marking code			HS1AB	HS1BB	HS1DB	HS1FB	HS1GB	HS1JB	HS1KB	HS1MB
Maximum Repetitive Peak Reverse Voltage	VRRM	V	50	100	200	300	400	600	800	1000
Maximum RMS Voltage	VRMS	V	35	70	140	210	280	420	560	700
Maximum DC blocking Voltage	VDC	V	50	100	200	300	400	600	800	1000
Average rectified output current @60Hz sine wave , resistance load , TL (Fig.1)	IO	A	1.0							
Forward Surge Current (Non-repetitive) @60Hz Half-sine wave , 1 cycle , Tj = 25	IFSM	A	30							
Forward Surge Current (Non-repetitive) @1ms , square wave , 1 cycle , Tj = 25			60							
Current squared time @1ms to 8.3ms Tj = 25	I²t	A²s	3.735							

Storage temperature



Electrical Characteristics T_a



Ordering Information (Example)

PREFERED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON
--------------	--------------	----------------	----------------------	-------------------------	--------------



HS1AB THRU HS1MB

ΩOutline Dimensions

DQ-214AA(SMB)		
Dim	Min	Max
A	1.85	2.15
B	3.30	3.94
C	4.05	4.75
68D	1.99	2.61
E	5.21	5.59
F	0.90	1.41

Ω Suggested pad layout



HS1AB THRU HS1MB

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability. A malfunction of with would directly endanger human life (such as medical instruments, transport equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <http://www.21yangjie.com>, or consult your nearest Yangjie office.