



- High efficiency
- High current capability
- High reliability
- High surge current capability
- Low power loss
- Glass passivated chip junction
- Solder dip 275 °C max. 7 s, per JESD 22-B106

- A-405

Forward Surge Current (Non-repetitive) @1ms, square wave, 1 cycle, Tj=25	FSM	A	@60
Current squared time @1ms≤t≤8.3ms Tj=25	I ² t	A ² s	
Typical junction capacitance @ Measured at 1MHz and Applied Reverse Voltage of 4.0 V.D.C	Cj	pF	

		UNIT	TEST CONDIT
Maximum instantaneous forward voltage drop per diode	V _F	V	I _{FM} =1.0

Maximum DC reverse current at
rated DC blocking voltage per
diode I_R μA T_j=25

Device marking code			1N4001GS	1N4002GS	1N4003GS	1N4004GS	1N4005GS	1N4006GS	1N4007GS
Maximum Repetitive Peak Reverse Voltage	V _{RRM}	V	50	100	200	400	600	800	1000
Maximum RMS Voltage	V _{RMS}	V	35	70	140	280	420	560	700
Maximum DC blocking Voltage	V _{DC}	V	50	100	200	400	600	800	1000

Average Forward Current
@60Hz sine wave, Resistance load, T_a I_{F(AV)} A 1.0
=75

v7KHUPDO &KDUDÄFWHUL8VQDHFVV RWKHUÄLVH VSHFLILHG

3\$5\$0(7(5	6<0%2/	81,7	1 *6	1 *6	1 *6	1 *6	1 *6	1 *6	1 *6
7\SLFDO 7KHUPDO	5H5LVWDQFH								

v2UGHULQJ ,QIRUPPSWLHRQ

35())(5(' 3 1	3\$&.\$*(&2'()	81,7 :(*,+7	0,1,080 3\$&.\$*(SF	,11(5 %2; 48\$17,7< S	287(5 &\$57; 48\$17,7< S	'(/,9(5< 02'()
1 *6 a 1 *6	'	\$SSUR[LPDWH	\$SSUR[LPDWH			
1 *6 a 1 *6	&	\$SSUR[LPDWH	\$SSUR[LPDWH			ty'ædxP•00 p,7<



■

Dim	Min	Max
A	4.22	5.21
B	2.03	2.72
C	25.4	/
D	0.53	0.64



The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.